

	SE36E	S20	A	1	00
SE36E Rotary Encoder					
Absolute Servo Motor Feedback					
Resolution					
S20	Single turn absolute 20-bit/revolution				
M36	Multi-turn absolute 20-bit/revolution and 16-bit number of turns				
Communication Interface					
A	ServoSense proprietary asynchronous protocol with 4 wires (free license)				
B	BiSS Safety serial protocol (free license)				
Mechanical Interface					
	Encoder Body	Rotor Shaft			
1	Set screw	Blind 6 mm hollow shaft with M3 axial screw			
2	Set screw	Blind 8 mm hollow shaft with M4 axial screw			
3	Resolver size 15 compatible	Blind 6 mm hollow shaft with M3 axial screw			
4	Resolver size 15 compatible	Blind 8 mm hollow shaft with M4 axial screw			
5	Resolver size 15 compatible	Blind 9.52 mm hollow shaft with M4 axial screw			
6	Resolver size 21 compatible	Blind 9.52 mm hollow shaft with M4 axial screw			
7	Resolver size 21 compatible	Blind 12.7 mm hollow shaft with M5 axial screw			
5	Customer-specific	Customer-specific			
Options					
00	Customization code				